



RECEIVER Handheld Receiver

IC-R30

- Decodes Digital Protocols (P25, NXDN™, dPMR™, D-STAR, DCR)
- 0.1-3304.999MHz Wideband Coverage
- Dualwatch Operation
- Dual Band Recording Function
- 2.3" Large LCD and Intuitive user interface
- 200 Channel Per Second High Speed Scan
- Integrated GPS receiver
- Band Scope Function
- Speech Function
- IP57 Rugged Construction
- Up to 8.3 Hours of Long Battery Life
- USB Charging and PC Connection
- Micro SD Card Slot for Voice and Data Storage
- Wireless Operation with a Bluetooth® headset



Accessories

Li-Ion battery Pack (BP287), Rapid Charger (BC223), AC Adaptor (BC123SE), USB cable for charging and data transfer, Telescopic antenna, Belt-clip (MN133) and Hand strap.

Order Code Description

| | |
|--------|--|
| IC-R30 | Handheld, 0.1-3304.999 MHz Modes: Decodes Digital Protocols (P25, NXDN™, dPMR™, D-STAR, DCR) |
|--------|--|

Batteries

| | |
|-------|--|
| BP287 | Li-ion, 3.6 V 3280 mAh (typ), 3120 mAh (min) (As Supplied) |
| BP293 | AA (LR6) x 3 battery case |

Battery Charger

| | |
|---------|---|
| BC223 | Charges the BP287 in 4 hours (approx.) (As Supplied) with BC123SV |
| BC123SV | AC Adaptor |

Earphone & Headphone

| | |
|------|--------------------|
| VS3 | Bluetooth® Headset |
| SP40 | Earphone |

Belt Clip & Carry Case

| | |
|-------|-------------------------|
| MB133 | Belt Clip (As Supplied) |
| LC189 | Carrying Case |

Programming Equipment

| | |
|--------|-------------------------------------|
| CS-R30 | Programming Software for Windows®PC |
|--------|-------------------------------------|